

WE DIDN'T BUILD IT TO KEEP YOUR BUSINESS COMPETITIVE.

**WE BUILT IT
TO PUT YOU
IN THE LEAD.**



Kodak

Scan Station 500

Add performance and power — in a small package — to your business.

Getting documents into the workflow fast is essential. Helping your business do more with those documents is even more important. That's why we built the **Kodak** Scan Station 500. It's a document scanning device loaded with smart features that make it easy to integrate, scan, and share.



E-mail



Fax



Network



Printer



Flash drive



FTP



The smart, fast, easy, friendly, quiet, secure Kodak Scan Station 500.

BUILT WITH A PURPOSE.

Send information. Not just data.

Our exclusive Voice Attachment feature gives you the option to record and send essential instructions with your documents.

Make sure everyone gets the message.

With one scan, send a document to the network, to e-mail, to the printer, to fax, to a USB drive, and to FTP — simultaneously!

Built to be Faster:

- Up to 9X faster than the competition (200 dpi, colour duplex mode)
- Scan up to 1,500 pages per day
- Robust and versatile paper handling
- Feeder tray accommodates up to 75 pages
- Single-pass, double-sided scanning saves time

Built to be Secure:

- Enable or disable scanning to portable flash drives
- User Authentication based upon standard **Windows OS** authentication
- Transaction log tracks all usage
- PDF private key encryption
- Secure login via LDAP

Built to be Easy to Use:

- Intuitive touchscreen operation
- Blank Page Removal instantly reduces file size
- Frequent job settings can be programmed for timesaving convenience
- Easy to configure remotely

- Kodak's Perfect Page Scanning for great image quality — automatically
- LDAP address lookup is compatible with your company directory
- Files can be named according to your company standards



The large 20.3 cm LCD touchscreen makes it easy for everyone to scan and share.

Built to be Office Friendly:

- Whisper-quiet operation
- Integrated fax/modem for send and receive operation — no need for a separate fax machine
- Scan and send with one device — no additional hardware or software required
- Ergonomically correct for standing or seated operation
- Ideal for walk-up or dedicated use

Built to Inspire Confidence:

The award-winning **Kodak** Service & Support professionals are always here to help keep your business running smoothly.



The Kodak Scan Station 500 delivers high performance in a space-saving footprint.

Kodak Scan Station 500

Connectivity	10/100 Base T and built-in 56K Fax Modem, no host PC required
Output Methods	Scan to network share, scan to print, scan to e-mail, scan to fax, scan to portable USB drive, scan to FTP (anonymous, authenticated, with proxy support)
Network Protocols	TCP/IP, SMB, authenticated SMTP (login, plain text, CRAM, NTLM), DHCP (or static), NT domain authentication
Security Features	PDF private key encryption, optional password access, option to enable/disable the ability to scan to portable USB drives, secure login via LDAP, activity logging by Login ID
File Format Outputs	Single and multipage TIFF, JPEG, PDF, text searchable PDF, encrypted PDF, optional JPEG compressed TIFF, WAV audio files
Control Panel	20.3 cm 800x400 TFT LCD with touchscreen
Audio	Built-in microphone and speaker to record and play back Voice Attachment messages
On-board Processor, Memory, Hard Drive	Intel Atom Processor 230 1.6GHz with 9456c chipset, 1 GB DDR2 667MHz RAM, 160GB STA 3 GB/sec hard drive
Scanning Technology	Duplex scanning with dual colour quadlinear CCD, 600 dpi optical resolution, capture bit depth is 30 bits (10 x 3), colour output bit depth is 24 bits (8 x 3), greyscale output bit depth is 256 levels (8-bit)
Output Resolution	75, 100, 150, 200, 240, 300, 400, 600 dpi
Imaging Features	Perfect Page Scanning, deskew, autotrim, content-based blank page removal
Throughput Speeds (portrait, DIN A4)	Black-and-white/greyscale/colour: up to 30 ppm/60 ipm at 200 dpi
Multi-Feed Detection	With ultrasonic technology
Feeder	Up to 75 sheets of 75 g/m ² paper
Maximum Document Size	215 mm x 863 mm - may be restricted at certain resolutions
Minimum Document Size	50 mm x 63.5 mm; Multiple-sheet feeding: 75 mm x 125 mm
Paper Thickness and Weight	52-413 g/m ² paper and ID cards up to 1.25 mm thick
Recommended Daily Volume	Up to 1,500 pages per day
Approvals and Product Certifications	AS/NZS 3548 Class A (C-Tick Mark), CAN/CSA-C22.2 No. 60950-1 (TUV C Mark), Canada ICES-003 Issue 3 (Class A), GB4943, GB9254 (Class A), GB 17625.1 Harmonics (CCC "S&E" Mark), EN 55022 ITE Emissions (Class A), EN 61000-3-3 Flicker, EN 55024 ITE Immunity (CE Mark), EN 60950 (TUV GS Mark), IEC 60950-1, CISPR 22 Class A, VCCI (Class A), CNS 13438 (Class A), CNS 14336 (BSMI Mark), UL 60950-1 (TUV US Mark), CFR 47 Part 15 Subpart B (FCC Class A), Argentina S-Mark
Dimensions	Weight: 10.5 kg; Depth 38.1 cm; Width: 34.9 cm; Height: 20.8 cm
What's in the Box	Kodak Scan Station 500, power cords, User's Guide, Setup & Documentation CD-ROMs, Quick Install Guide, one portable USB drive, configuration organizer software
Accessories Available	Portable USB drives, Kodak Scan Station 500 Keyboard and Stand Accessory, Kodak A3 Flatbed Accessory, Kodak A4 Flatbed Accessory
Consumables Available	Feed modules, roller cleaning pads, Staticide Wipes
Software Available	NSi AutoStore Client enabled, other NSi AutoStore applications available
Warranty*	12 months Warranty with Advanced Unit Replacement (AUR) in 4 business days and Scanner Hotline Support
Warranty Enhancement*	36 months Warranty with Advanced Unit Replacement (AUR) next business day and Scanner Hotline Support
Recommended portable USB drive specs	USB 2.0, minimum size for configuration: 32 MB, minimum size for storing images/files: 128 MB
Environmental Factors	Operating temperature: 10-35° C; Operating humidity: 10% to 85% RH, Altitude <2000M
Illumination	Dual Fluorescent (Cold Cathode)
Power Consumption	Standby: <6 Watts; Operating: <95 Watts
Interfaces	On rear panel: four USB 2.0 ports, one RJ45 10/100 Base T Ethernet port, one custom flatbed port and one RJ11 telephone jack On bezel: one USB 2.0 port

*There may be geographical limitations to the availability of Services. For full details please contact your Reseller of Kodak products or your local Kodak Service & Support organisation.



To learn more:

www.kodak.com/go/getyourScanStation

Printed using Kodak Technologies.

United Kingdom, Phone: +44 870 8502351, Fax: +44 870 850 2352
Nordic, Phone: +46 (8) 555 638 31, Fax: +46 (8) 555 995 04
Africa, Phone: +44 1442 846547, Fax: +44 1442 846606
Germany, Austria and Switzerland, Phone: +49 711 406 2535, Fax: +49 711 406 3619
Eastern Europe, Near and Middle East, Phone: +36 1 454 3031, Fax: +36 1 387 9113
France, Spain and Portugal, Phone: +33 1 4001 3180, Fax +33 1 4001 3981
Italy, Phone: +39 0266028338, Fax: +39 0266028358
The Netherlands, Phone: +31 33 2998751, Fax: +31 20 6545227
Belgium and Luxembourg, Phone: +32 2 352 27 04, Fax: +32 2 352 30 28

©Kodak, 2009. Kodak is a trademark of Kodak. DoldeMedien 020_09

Subject to technical change without notice.
CAT No. E-DI.035.0209.en.01